

where the world turns for

**Lovejoy**

*Couplings*

# Grid

## In This Section:

- Horizontal Cover Style
- Vertical Cover Style
- Full Spacer Style
- Half Spacer Style



GD

## Grid

### Safety Warning

When using Lovejoy products, you must follow these instructions and take the following precautions. Failure to do so may cause the power transmission product to break and parts to be thrown with sufficient force to cause severe injury or death.

Refer to this Lovejoy Catalog for proper selection, sizing, horsepower, torque range, and speed range of power transmission products, including elastomeric elements for couplings. Follow the installation instructions included with the product, and in the individual product catalogs for proper installation of power transmission products. Do not exceed catalog ratings.

During start up and operation of power transmission product, avoid sudden shock loads. Coupling assembly should operate quietly and smoothly. If coupling assembly vibrates or makes beating sound, shut down immediately, and recheck alignment. Shortly after initial operation and periodically thereafter, where applicable, inspect coupling assembly for: alignment, wear of elastomeric element, bolt torques, and flexing elements for signs of fatigue. Do not operate coupling assembly if alignment is improper, or where applicable, if elastomeric element is damaged, or worn to less than 75% of its original thickness.

Do not use any of these power transmission products for elevators, man lifts, or other devices that carry people. If the power transmission product fails, the lift device could fall resulting in severe injury or death.

For all power transmission products, you must install suitable guards in accordance with OSHA and American Society of Mechanical Engineers Standards. Do not start power transmission product before suitable guards are in place. Failure to properly guard these products may result in severe injury or death from personnel contacting moving parts or from parts being thrown from assembly in the event the power transmission product fails.

If you have any questions, contact the Lovejoy Engineering Department at 1-630-852-0500.



# Grid

## Table of Contents

|  | Running<br>Page No. | Section<br>Page No. |
|--|---------------------|---------------------|
| Overview.....  | 216                 | GD-4                |
| Selection Process.....   | 217                 | GD-5                |
| Application Service Factors > Selection Data .....               | 219                 | GD-7                |
| Grid Coupling Selection Worksheet.....                           | 221                 | GD-9                |
| Standard Coupling > Performance Data .....                       | 222                 | GD-10               |
| Standard Coupling > Dimensional Data .....                       | 223                 | GD-11               |
| Spacer Style > Performance / Dimensional Data .....              | 224                 | GD-12               |
| Spacer Style > Spacer Hub Selection .....                        | 225                 | GD-13               |
| Misalignment Capability > Item Selection.....                    | 226                 | GD-14               |
| Industry Standard Interchange Chart > Item Selection .....       | 227                 | GD-15               |
| Grid Coupling Hubs – Inch Bore / Keyway > Item Selection .....   | 228                 | GD-16               |
| Grid Coupling Hubs – Metric Bore / Keyway > Item Selection ..... | 229                 | GD-17               |
| Grid Coupling – Taper Lock Hubs > Item Selection.....            | 230                 | GD-18               |
| Grid Coupling – Component Part Numbers > Item Selection.....     | 231                 | GD-19               |

### The Power of Torsional Dampening

Lovejoy is pleased to be able to provide quality grid couplings covering a large number of industry standard sizes and lengths. The Lovejoy grid style coupling has proven itself in performance and popularity over a wide range of applications.

Lovejoy's grid style coupling design has demonstrated its ability to dampen vibration by as much as 30% and can cushion shock loads that could cause damage to both the driving and driven equipment. The tapered grid spring design absorbs impact energy by spreading the energy out over the full length of the grid spring thus reducing the magnitude of the torque spikes.

The Lovejoy design uses a curved hub tooth profile which creates a progressive contact with the flexible grid spring as the application torque increases. This feature provides a more effective and efficient transmission of power in properly aligned couplings.

Lovejoy's versatile design of industry standard hubs and grid springs for both horizontal and vertical cover styles allow Lovejoy couplings to be interchangeable with other industry standard grid couplings and components.

Proper grid coupling installation and maintenance can add to a longer coupling life. Grid spring replacement is simple and can be performed at a fraction of the cost and time of a complete coupling.

#### GD

#### Features

- High tensile, shot-peened alloy steel grid springs and precision machined hubs ensure superior coupling performance and long life.
- Lovejoy's grid couplings with tapered grids are designed to be interchangeable with other industry standard grid couplings with both horizontal and vertical grid covers.
- Lovejoy grid couplings are designed for ease of installation and maintenance reducing labor and downtime costs.
- The torsional flexibility and resilience of Lovejoy grid couplings helps reduce vibration and cushions shock and impact loads.
- Cover fasteners can be provided in either Inch or Metric sizes.
- Excellent for use in applications where the equipment is close coupled or spaced apart requiring a spacer style coupling arrangement.
- Stock spacer designs are available or requests for custom spacer lengths can be addressed by Lovejoy engineering.



#### WARNING

You must refer to page GD-2 (page 214) for Important Safety Instructions and Precautions for the selection and use of these products. Failure to follow the instructions and precautions could lead to severe injury or death.



#### Horizontal Split Cover Design

- Ideal for limited space
- Allows easy access to the grid spring
- Well suited for reversing applications
- Lightweight die-cast aluminum grid cover



#### Vertical Split Cover Design

- Ideal for higher operating speeds
- Allows easy access to the grid spring
- Cover is manufactured from stamped steel for strength



#### Full Spacer Design – Horizontal Cover

- Drop-out design ideal for pump applications and servicing
- Stock sizes 1020 thru 1090
- Lightweight die-cast aluminum grid cover



#### Half Spacer Design – Horizontal Cover

- Offers additional BSE dimensions
- Lightweight die-cast aluminum grid cover

### Grid Coupling Selection Process

The following information is necessary when making a Grid coupling selection:

- Description of motor or engine, the horse power (or KW), and RPM at slowest coupling speed while under load
- Description of the driven equipment
- Shaft and keyway sizes and the type of fit for driver and driven equipment (clearance or interference)\*\*
- Shaft separation (BSE)
- Physical space limitations (see Application Worksheet)
- Determine what the environmental conditions will be, such as temperature, corrosive conditions, interference from surrounding structures, etc.

\*\* By default, sizes 1020 – 1090 will be clearance fit, sizes 1100 – 1200 will be interference fit.

\*\* Lovejoy machines all bores and keyways to meet the dimensional and tolerance specifications per ANSI/AGMA 9002-B04 for inch bores, or ISO 286-2 for metric bores.

Typical grid couplings consist of two grid hubs, a grid spring, and a cover assembly. When the shaft separation requires a spacer style coupling, the coupling will consist of two shaft hubs, two spacer hubs, a grid spring, and a horizontal cover assembly.

The following charts are available to assist in making the best possible grid coupling selection:

- |  |                       |
|--|-----------------------|
| ■ Coupling Selection Worksheet,                                | Page GD-9             |
| ■ Grid Standard Interchange Chart,                             | Page GD-15            |
| ■ Application Service Factors,                                 | Pages GD-7 and GD-8   |
| ■ General Service Factors,                                     | Page GD-6 (bottom)    |
| ■ Performance and Dimensional Data for Standard Grid Couplings | Page GD-10 thru GD-11 |
| ■ Performance and Dimensional Data for Spacer Grid Couplings   | Page GD-12            |
| ■ Grid Coupling Part Numbers for Standard Components           | Page GD-16 thru GD-19 |

#### Formulas Used To Calculate Torque:

$$\text{Application Torque (in-lbs)} = \left( \frac{\text{horse power} \times 63025}{\text{RPM}} \right)$$

$$\text{Application Torque (Nm)} = \left( \frac{\text{horse power} \times 9550}{\text{RPM}} \right)$$

$$\text{Selection Torque} = \text{Application Torque} \times \text{Service Factor}$$

#### High Peak Loads and Brake Applications

For applications where high peak loads or high braking torques might be present, the following additional information will be necessary:

- System peak torque and frequency
- Duty cycle
- Brake torque rating

The selection torque formula is similar to the formula shown above except that the application torque should be doubled prior to applying the service factor.

$$\text{Application Torque (in-lbs)} = \left( \frac{\text{horse power} \times 63025}{\text{RPM}} \right)$$

$$\text{Application Torque (Nm)} = \left( \frac{\text{horse power} \times 9550}{\text{RPM}} \right)$$

$$\text{Selection Torque} = 2 \times \text{Application Torque} \times \text{Service Factor}$$

Please feel free to contact Lovejoy Application Engineering or Technical Support for assistance with additional grid coupling questions.

### Steps In Selecting A Grid Coupling

**Step 1:** Determine the application torque using the formula shown above.

**Step 2:** Select the Service Factor from the charts on pages GD-7 and GD-8. For applications not displayed use the chart shown to the right. Determine the Selection Torque using the formula shown above.

**Step 3:** Using the selection torque as calculated, refer to the Performance Chart on page GD-10 to determine the minimum size grid coupling that will accommodate the torque.

**Step 4:** Compare the maximum bore for the size selected and ensure the required bore sizes do not exceed the maximum allowable. If the required bore size is larger, step up to the next size coupling and check to see if the bore sizes will fit.

**Step 5:** Using the selected coupling size, compare the bore and keyway sizes with the charts located on pages GD-16 thru GD-17 for UPC part numbers.

**Step 6:** Contact your local industrial supplier with the part numbers to place your order.

See the Selection Example process on the next page.

## Selection Example

### Application Description

A company would like to use a grid coupling to connect a standard AC electric motor to a rotary lobe compressor. The electric motor is rated for 60 horsepower running at 1,760 RPM. The shaft size on the electric motor (driver) is 2-1/8 inches with a standard 1/2" square key. The shaft size on the compressor (driven) is 48 millimeters with a standard 14mm key. Both the motor and compressor shaft are 3 inches long and the gap (BSE) between the shaft ends is 1/8 inch.

The following steps provide an excellent selection process that will work for most standard grid coupling selections. For assistance in this selection process, feel free to contact Lovejoy Application Engineering or Technical Support.

**Step 1:** Using the information provided by the customer, determine the application torque:

$$\text{Application Torque (in-lbs)} = \left( \frac{\text{horse power} \times 63025}{\text{RPM}} \right)$$

for this example:

$$\text{Application Torque (in-lbs)} = \left( \frac{60 \times 63025}{1,760} \right) = 2,149 \text{ in-lbs}$$

**Step 2:** Select the application service factor from the chart on pages GD-7 and GD-8 to determine which value best corresponds to an electric motor driven rotary lobe style compressor. In the charts find the application category 'Compressors', 'Rotary lobe and vane', and under the column for 'Electric Motors', is the service factor number 1.25.

If the service factor did not appear on the service factor charts for the defined application, a generic value could be selected from the chart located on the right side of this page.

**Step 3:** Calculate the Selection Torque for the application:

$$\text{Selection Torque} = \text{Application Torque} \times \text{Service Factor}$$

$$\text{Selection Torque} = 2,149 \text{ in-lbs} \times 1.25 = 2,687 \text{ in-lbs}$$

**Step 4:** Reference the Grid Coupling Performance and Dimensional data on pages GD-10 and GD-11. Use the Selection Torque to make an initial selection based on the nominal torque allowed for the coupling size. The first coupling size that can accommodate 2,687 in-lbs or torque is the size 1050 grid coupling with a nominal torque rating of 3,850 in-lbs.

**Step 5:** Note, that the electric motor's 2-1/8 inch shaft diameter exceeds the maximum allowable bore size for a size 1050 coupling which is 1-7/8 inches. Using the same chart, scan the column for maximum bore sizes and find the first coupling size larger than the 1050 that will accommodate the 2-1/8 inch bore size. The size 1060 coupling will accommodate the 2-1/8 inch bore. The horizontal cover can be selected since the application speed of 1,760 RPM does not exceed the coupling's maximum speed of 4,350 RPM.

**Step 6:** Prior to finalizing the 1060 selection, it is always a good idea to review all of the coupling details to ensure the correct coupling has been selected. The following are the comparisons usually made.

|              | 1060 Coupling | Application  | Acceptable? |
|--------------|---------------|--------------|-------------|
| Torque:      | 6,050 in-lbs  | 2,687 in-lbs | yes         |
| Bore Size:   | 2-1/8" max    | 2-1/8"       | yes         |
| BSE          | 0.13"         | 1/8"         | yes         |
| Speed        | 4,350 RPM     | 1,760 RPM    | yes         |
| Mount length | 5.13" OAL     | 6-1/8"       | yes         |

Check the Grid Series Misalignment Chart to ensure the application meets the misalignment requirements. If the items above are acceptable and the application misalignment falls within the allowable range of the 1060 grid coupling, the 1060 grid coupling appears to be the correct coupling for this application.

**Step 7:** Using the UPC Selection tables on Pages GD-16 thru GD-19, find the required hubs for the corresponding coupling size and the required Cover and Grid Assembly.

|  |                           |
|--|---------------------------|
| 1060 Hub Bore 2-1/8"                                       | see page GD-16, use 05491 |
| 1060 Hub Bore 48mm   | see page GD-17, use 05815 |
| 1060 Horizontal Cover and Grid assembly with inch hardware | see page GD-19, use 05353 |

Prefix all grid coupling part numbers with 697904

### General Service Factors

| Typical Applications for Electric Motor or Turbine Driven Equipment   | Typical Service Factor |
|---|------------------------|
| Constant Torque such as Centrifugal Pumps, Blowers, and Compressors.  | 1.0                    |
| Continuous Duty with some torque variations including Printing Presses, Extruders, Forced Draft Fans.   | 1.5                    |
| Light shock loads from Briquetting Machine, Rubber Calendar, or Crane and Hoist.  | 2.0                    |
| Moderate shock loading as expected from a Car Dumper, Reciprocating Feeder, or Vibrating Screen.  | 2.5                    |
| Heavy Shock load with some negative torques from Crushers, Manipulators, and Braking Drum.  | 3.0                    |
| For applications like Reciprocating Compressors with frequent torque reversals which do not necessarily cause reverse rotations, contact Lovejoy Technical Support. |                        |

Application Service Factors

Chart 1

|   | Service Factors                      |                                       |  |  | Service Factors                      |                                       |  |  | Service Factors                      |                                       |  |
|---|--------------------------------------|---------------------------------------|--|--|--------------------------------------|---------------------------------------|--|--|--------------------------------------|---------------------------------------|--|
|   | Electric Motor w/<br>Standard Torque | Reciprocating<br>Engines-4/5 Cylinder | Reciprocating<br>Engines-6 or more Cyl |  | Electric Motor w/<br>Standard Torque | Reciprocating<br>Engines-4/5 Cylinder | Reciprocating<br>Engines-6 or more Cyl |  | Electric Motor w/<br>Standard Torque | Reciprocating<br>Engines-4/5 Cylinder | Reciprocating<br>Engines-6 or more Cyl |
| <b>Aggregate Processing, Cement, Mining Kilns; Tube, Rod and Ball Mills</b>   |                                      |                                       |  | Coilers (Up or Down) Cold Mills only, Cooling Beds, Mill Tables Hot Bed or   |                                      |                                       |  | Couch, Cylinder, Dryer, Pulp Grinder, Fourdrinier, Press, Suction Roll.....  | 1.75                                 | 2.75                                  | 2.25                                   |
| Dryer, Rotary, Hammermill or Hog, Tumbling Mill or Barrel, Direct or on L.S. Shaft of Reducer, with Final Drive of Single Helical or Herringbone Gears... | 1.75                                 | 2.75                                  | 2.25                                   | Transfer, Non-Reversing .....  | 1.50                                 | 2.50                                  | 2.00                                   | Barker Auxiliary, Hydraulic, Mechanical, Barking Drum L.S. Shaft of Reducer with Final Drive-Helical or Herringbone Gear, Cutter, Felt Whipper, Jordan, Log Haul ..... | 2.00                                 | 3.00                                  | 2.50                                   |
| Grizzly, Direct or on L.S. Shaft of Reducer, with Final Drive of Machined Spur Gears.....   | 2.00                                 | 3.00                                  | 2.50                                   | Reel Drives, Slitters, Steel Mill only, Wire Drawing Machinery..   | 1.75                                 | 2.75                                  | 2.25                                   | Barking Drum L.S. Shaft of Reducer with Final Drive-Machined Spur Gear, Chipper..  | 2.50                                 | *                                     | *                                      |
| Crushers, Ore or Stone .....  | 2.50                                 | *                                     | *                                      | Coilers (Up or Down) Hot Mills only, Coke Plants Door Opener, Drawbench, Furnace Pushers, Hot and Cold Saws, Ingot Cars, Mill Tables Runout, Non-Reversing, Non-Plugging, Screwdown, Seamless Tube Mills -Thrust Block, Tube Conveyor Rolls, Reeler, Kick Out, Soaking Pit Cover Drives - Travel, Straighteners, |                                      |                                       |  | Barking Drum L.S. Shaft of Reducer with Final Drive-Cast Tooth Spur Gear .....   | 3.00                                 | *                                     | *                                      |
| <b>Brewing and Distilling</b>   |                                      |                                       |  | Unscramblers.....  | 2.00                                 | 3.00                                  | 2.50                                   | <b>Rubber Industry</b>   |                                      |                                       |  |
| Bottle and Can Filling Machines, Brew Kettle.....   | 1.00                                 | 2.00                                  | 1.50                                   | Coke Plants Pusher Ram Drive, .....  | 2.50                                 | *                                     | *                                      | Tire/Tube Press Opener (Peak Torque).....  | 1.00                                 | 2.00                                  | 1.50                                   |
| Cookers, Continuous Duty, Mash Tub .....  | 1.25                                 | 2.25                                  | 1.75                                   | Coke Plants Pusher or Larry Car Traction Drive, Feed Rolls-Blooming Mills, Manipulators, Mill Tables Roughing Breakdown Mills, Runout, Reversing, Seamless Tube Mills Piercer, Sideguards .....  | 3.00                                 | *                                     | *                                      | Extruder, Mixing Mill, Refiner or Sheeter (Five or More in Line), Tuber, Strainer, Pelletizer, Warming Mill (Three or More in Line) .....                              | 1.75                                 | 2.75                                  | 2.25                                   |
| Lauter Tub.....   | 1.50                                 | 2.50                                  | 2.00                                   | Cold Mills, Hot Mills, Merchant Mills, Rod Mills, Skelp Mills.....   | Refer To Lovejoy                     |                                       |  | Calender, Mixing Mill, Refiner or Sheeter (Three/Four in Line), Warming Mill (One/Two in Line) .....   | 2.00                                 | 3.00                                  | 2.50                                   |
| Scale Hopper, Frequent Peaks ...  | 1.75                                 | 2.75                                  | 2.25                                   | <b>Oil Industry</b>  |                                      |                                       |  | Cracker, Plasticator, Mixing Mill, Refiner or Sheeter (One/Two in line), Intensive or Banbury Mixer, Tire Building Machine, Washer .....                               | 2.50                                 | *                                     | *                                      |
| <b>Clay Working Industry</b>  |                                      |                                       |  | Chiller.....   | 1.25                                 | 2.25                                  | 1.75                                   | <b>Sewage Disposal Equipment</b>   |                                      |                                       |  |
| Brick Press, Briquette Machine, Clay Working Machine, Plug Mill.....  | 1.75                                 | 2.75                                  | 2.25                                   | Paraffin Filter Press .....  | 1.50                                 | 2.50                                  | 2.00                                   | Bar Screen, Chemical Feeders, Collectors, Dewatering Screen, Grit Collector .....  | 1.00                                 | 2.00                                  | 1.50                                   |
| <b>Dredges</b>  |                                      |                                       |  | Oilwell Pumping (not over 150% Peak Torque), Rotary Kiln.....  | 2.00                                 | 3.00                                  | 2.50                                   | <b>Sugar Industry</b>  |                                      |                                       |  |
| Conveyors.....  | 1.25                                 | 2.25                                  | 1.75                                   | <b>Paper Mills</b>   |                                      |                                       |  | Mill Stands, Turbine Driven with all Helical or Herringbone Gears .....  | 1.50                                 | 2.50                                  | 2.00                                   |
| Maneuvering Winch, Pumps (Uniform Load), Utility Winch....  | 1.50                                 | 2.50                                  | 2.00                                   | Bleachers, Coaters, Stock Pumps, Centrifugal Constant Speed.....   | 1.00                                 | 2.00                                  | 2.50                                   | Cane Carrier & Leveler, Electric Drive or Steam Engine Drive with Helical Herringbone, or Spur Gears with any Prime Mover .....  | 1.75                                 | 2.75                                  | 2.25                                   |
| Cable Reel, Screen Drive, Stacker .....   | 1.75                                 | 2.75                                  | 2.25                                   | Converting Machine, Felt Stretcher, Stock Pumps, Centrifugal Frequent Speed Changes Under Load .....   | 1.25                                 | 2.25                                  | 1.75                                   | Cane Knife & Crusher.....  | 2.00                                 | 3.00                                  | 2.50                                   |
| Cutter Head, Jig Drive .....  | 2.00                                 | 3.00                                  | 2.50                                   | Line Shaft, Reel, Rewinder, Winder, Stock Chest, Washer, Thickener .....   | 1.50                                 | 2.50                                  | 2.00                                   |  |                                      |                                       |  |
| <b>Food Industry</b>  |                                      |                                       |  | Beater, Pulper, Calender,  |                                      |                                       |  |  |                                      |                                       |  |
| Bottling, Can Filling Machine.....  | 1.00                                 | 2.00                                  | 1.50                                   |  |                                      |                                       |  |  |                                      |                                       |  |
| Cereal Cooker.....  | 1.25                                 | 2.25                                  | 1.75                                   |  |                                      |                                       |  |  |                                      |                                       |  |
| Beet Slicer, Dough Mixer, Meat Grinder.....   | 1.75                                 | 2.75                                  | 2.25                                   |  |                                      |                                       |  |  |                                      |                                       |  |
| <b>Lumber</b>   |                                      |                                       |  |  |                                      |                                       |  |  |                                      |                                       |  |
| Rolls, Non-Reversing, Sawdust Conveyor.....   | 1.25                                 | 2.25                                  | 1.75                                   |  |                                      |                                       |  |  |                                      |                                       |  |
| Band Resaw, Sorting Table .....   | 1.50                                 | 2.50                                  | 2.00                                   |  |                                      |                                       |  |  |                                      |                                       |  |
| Circular Resaw, Cut-off, Planer, Slab Conveyor, Trimmer .....   | 1.75                                 | 2.75                                  | 2.25                                   |  |                                      |                                       |  |  |                                      |                                       |  |
| Edger, Head Rig, Hog, Log Haul, Rolls, Reversing .....  | 2.00                                 | 3.00                                  | 2.50                                   |  |                                      |                                       |  |  |                                      |                                       |  |
| Gang Saw (Reciprocating).....   | Refer To Lovejoy                     |                                       |  |  |                                      |                                       |  |  |                                      |                                       |  |
| <b>Metal Rolling Mills<sup>1</sup></b>  |                                      |                                       |  |  |                                      |                                       |  |  |                                      |                                       |  |
| Soaking Pit Cover Drives - Lift ....  | 1.00                                 | 2.00                                  | 1.50                                   |  |                                      |                                       |  |  |                                      |                                       |  |

Notes: ■ 1 indicates: For high peak load applications, please refer to selection process on page GD-5.

■ \* indicates: That Lovejoy Application Engineering should be consulted with specific requirements.

■ Caution: Applications involving reciprocating engines and reciprocating driven devices are subject to critical rotational speeds which may damage the coupling and/or connected equipment. Contact Lovejoy Application Engineering with specific requirements.

Application Service Factors

Chart 1, Continued

|  | Electric Motor w/<br>Standard Torque | Reciprocating<br>Engines-4/5 Cylinder | Reciprocating<br>Engines-6 or more Cyl |   | Electric Motor w/<br>Standard Torque | Reciprocating<br>Engines-4/5 Cylinder | Reciprocating<br>Engines-6 or more Cyl |  | Electric Motor w/<br>Standard Torque | Reciprocating<br>Engines-4/5 Cylinder | Reciprocating<br>Engines-6 or more Cyl |
|--|--------------------------------------|---------------------------------------|--|---|--------------------------------------|---------------------------------------|--|--|--------------------------------------|---------------------------------------|--|
| <b>Textile Industry</b>                          |                                      |                                       |  | <b>Cranes, Hoist<sup>1, 2</sup></b>                 |                                      |                                       |  | Machine, Forming Mills.....2.00 3.00 2.50        |                                      |                                       |  |
| Batcher, Dyeing Machinery,                       |                                      |                                       |  | Slope.....1.50 2.50 2.00                            |                                      |                                       |  | <b>Mixers (see Agitators)</b>                    |                                      |                                       |  |
| Mangle, Napper, Soaper.....1.25 2.25 1.75        |                                      |                                       |  | Main or Skip Hoist, Bridge,                         |                                      |                                       |  | Muller .....1.50 2.50 2.00                       |                                      |                                       |  |
| Calender, Card Machine, Cloth                    |                                      |                                       |  | Travel, Trolley <sup>2</sup> .....1.75 2.75 2.25    |                                      |                                       |  | Concrete .....1.75 2.75 2.25                     |                                      |                                       |  |
| Finishing Machine, Dry Can,                      |                                      |                                       |  | <b>Dynamometer</b> .....1.00 2.00 1.50              |                                      |                                       |  | <b>Printing Press</b> .....1.50 2.50 2.00        |                                      |                                       |  |
| Loom, Spinner, Tenter Frame,                     |                                      |                                       |  | <b>Elevators<sup>2</sup></b>                        |                                      |                                       |  | <b>Pug Mill</b> .....1.75 2.75 2.25              |                                      |                                       |  |
| Winder.....1.50 2.50 2.00                        |                                      |                                       |  | Bucket, Centrifugal, Discharge,                     |                                      |                                       |  | <b>Pulverizers</b>                               |                                      |                                       |  |
| Knitting Machine.....Refer To Lovejoy            |                                      |                                       |  | Gravity Discharge .....1.25 2.25 1.75               |                                      |                                       |  | Roller.....1.50 2.50 2.00                        |                                      |                                       |  |
|  |                                      |                                       |  | Freight or Passenger.....NOT APPROVED               |                                      |                                       |  | Hammermill, Hog.....1.75 2.75 2.25               |                                      |                                       |  |
| <b>Applications</b>                              |                                      |                                       |  | <b>Escalators</b> .....NOT APPROVED                 |                                      |                                       |  | <b>Pumps</b>                                     |                                      |                                       |  |
| <b>Aerator</b> .....2.00 3.00 2.50               |                                      |                                       |  | <b>Exciter, Generator</b> .....1.00 2.00 1.50       |                                      |                                       |  | Centrifugal Constant Speed .....1.00 2.00 1.50   |                                      |                                       |  |
| <b>Agitators</b>                                 |                                      |                                       |  | <b>Extruder, Plastic</b> .....1.50 2.50 2.00        |                                      |                                       |  | Centrifugal Frequent Speed                       |                                      |                                       |  |
| Vertical/Horizontal Screw, Pro-                  |                                      |                                       |  | <b>Fans</b>   |                                      |                                       |  | Changes under Load, Descaling,                   |                                      |                                       |  |
| peller, Paddle .....1.00 2.00 1.50               |                                      |                                       |  | Centrifugal, Forced Draft Motor                     |                                      |                                       |  | w/ Accumulators, Gear, Rotary,                   |                                      |                                       |  |
| <b>Barge Haul Puller</b> .....1.50 2.50 2.00     |                                      |                                       |  | Driven thru Fluid or Electric Slip                  |                                      |                                       |  | Vane .....1.25 2.25 1.75                         |                                      |                                       |  |
| <b>Blowers</b>                                   |                                      |                                       |  | Clutch .....1.00 2.00 1.50                          |                                      |                                       |  | Reciprocating, 3 or more                         |                                      |                                       |  |
| Centrifugal.....1.00 2.00 1.50                   |                                      |                                       |  | Induced Draft with Damper Con-                      |                                      |                                       |  | Cylinders .....1.50 2.50 2.00                    |                                      |                                       |  |
| Lobe, Vane.....1.25 2.25 1.75                    |                                      |                                       |  | trol or Blade Cleaner.....1.25 2.25 1.75            |                                      |                                       |  | Reciprocating, 2 Cyl. Double                     |                                      |                                       |  |
| <b>Car Dumpers</b> .....2.50 * *                 |                                      |                                       |  | Forced Draft-Across the Line                        |                                      |                                       |  | Acting .....1.75 2.75 2.25                       |                                      |                                       |  |
| <b>Car Pullers</b> .....1.50 2.50 2.00           |                                      |                                       |  | start, Gas Recirculating .....1.50 2.50 2.00        |                                      |                                       |  | Reciprocating, 2 Cyl. Single                     |                                      |                                       |  |
| <b>Clarifier, Classifier</b> .....1.00 2.00 1.50 |                                      |                                       |  | Cooling Tower, Induced Draft                        |                                      |                                       |  | Acting .....2.00 3.00 2.50                       |                                      |                                       |  |
| <b>Compressors</b>                               |                                      |                                       |  | without Controls .....2.00 3.00 2.50                |                                      |                                       |  | Reciprocating, 1 Cyl. Single/                    |                                      |                                       |  |
| Centrifugal, Rotary, Screw.....1.00 2.00 1.50    |                                      |                                       |  | <b>Feeders</b>                                      |                                      |                                       |  | Double Acting.....3.00 * *                       |                                      |                                       |  |
| Rotary, Lobe or Vane .....1.25 2.25 1.75         |                                      |                                       |  | Apron, Belt, Disc, Screw.....1.00 2.00 1.50         |                                      |                                       |  | <b>Screens</b>                                   |                                      |                                       |  |
| Reciprocating with Flywheel and                  |                                      |                                       |  | Reciprocating.....2.50 * *                          |                                      |                                       |  | Air Washing, Water.....1.00 2.00 1.50            |                                      |                                       |  |
| Gear between Compressor and                      |                                      |                                       |  | <b>Generators</b>                                   |                                      |                                       |  | Rotary Coal, Sand .....1.50 2.50 2.00            |                                      |                                       |  |
| Prime Mover 4 or More Cyl.                       |                                      |                                       |  | Even Load.....1.00 2.00 1.50                        |                                      |                                       |  | Grizzly .....2.00 3.00 2.50                      |                                      |                                       |  |
| Single/Double Acting.....1.75 2.75 2.25          |                                      |                                       |  | Hoist or Railway Service.....1.50 2.50 2.00         |                                      |                                       |  | Vibrating.....2.50 * *                           |                                      |                                       |  |
| Reciprocating with flywheel                      |                                      |                                       |  | Welder Load .....2.00 3.00 2.50                     |                                      |                                       |  | <b>Ski Tows, Lifts</b> .....NOT APPROVED         |                                      |                                       |  |
| and Gear between Compressor                      |                                      |                                       |  | <b>Hammermill</b> .....1.75 2.75 2.25               |                                      |                                       |  | <b>Steering Gear</b> .....1.00 2.00 1.50         |                                      |                                       |  |
| and Prime Mover Cyl. Double                      |                                      |                                       |  | <b>Laundrywasher or Tumbler</b> .....2.00 3.00 2.50 |                                      |                                       |  | <b>Stoker</b> .....1.00 2.00 1.50                |                                      |                                       |  |
| Acting .....2.00 3.00 2.50                       |                                      |                                       |  | <b>Line Shafts</b>                                  |                                      |                                       |  | <b>Tumbling Barrel</b> .....1.75 2.75 2.25       |                                      |                                       |  |
| Reciprocating with Flywheel and                  |                                      |                                       |  | Any Processing Machinery.....1.50 2.50 2.00         |                                      |                                       |  | <b>Winch, Maneuvering</b>                        |                                      |                                       |  |
| Gear between Compressor and                      |                                      |                                       |  | <b>Machine Tools</b>                                |                                      |                                       |  | Dredge, Marine.....1.50 2.50 2.00                |                                      |                                       |  |
| Prime Mover 1/2 Cyl. Single/                     |                                      |                                       |  | Auxiliary, Traverse Drive.....1.00 2.00 1.50        |                                      |                                       |  | <b>Windlass</b> .....1.50 2.50 2.00              |                                      |                                       |  |
| Double Acting and 3 cyl.                         |                                      |                                       |  | Main Drive.....1.50 2.50 2.00                       |                                      |                                       |  | <b>Woodworking Machinery</b> .....1.00 2.00 1.50 |                                      |                                       |  |
| Single Acting .....3.00 * *                      |                                      |                                       |  | Bending Roll, Notching Press,                       |                                      |                                       |  | <b>Work Lift Platforms</b> .....NOT APPROVED     |                                      |                                       |  |
| Reciprocating Direct Connected,                  |                                      |                                       |  | Punch Press, Planer, Plate                          |                                      |                                       |  |  |                                      |                                       |  |
| Without Flywheels..... Refer To                  |                                      |                                       |  | Reversing.....1.75 2.75 2.25                        |                                      |                                       |  |  |                                      |                                       |  |
| Lovejoy  |                                      |                                       |  | <b>Manlifts</b> .....NOT APPROVED                   |                                      |                                       |  |  |                                      |                                       |  |
| <b>Conveyors<sup>2</sup></b>                     |                                      |                                       |  | <b>Metal Forming Machines</b>                       |                                      |                                       |  |  |                                      |                                       |  |
| Apron, Assembly, Belt, Chain,                    |                                      |                                       |  | Slitters .....1.00 2.00 1.50                        |                                      |                                       |  |  |                                      |                                       |  |
| Flight, Screw .....1.00 2.00 1.50                |                                      |                                       |  | Wire Winder, Coilers, Uncoilers...1.50 2.50 2.00    |                                      |                                       |  |  |                                      |                                       |  |
| Bucket.....1.25 2.25 1.75                        |                                      |                                       |  | Wire Drawing, Flattening .....1.75 2.75 2.25        |                                      |                                       |  |  |                                      |                                       |  |
| Live Roll, Shaker,                               |                                      |                                       |  | Draw Bench Carriage, Main                           |                                      |                                       |  |  |                                      |                                       |  |
| Reciprocating .....3.00 * *                      |                                      |                                       |  | Drive, Extruder, Forming                            |                                      |                                       |  |  |                                      |                                       |  |


Notes: ■ 1 indicates: For high peak load applications, please refer to selection process on page GD-5.  
 ■ 2 indicates: If people are transported Lovejoy does not recommend and will not warranty the use of the coupling.  
 ■ \* indicates: That Lovejoy Application Engineering should be consulted with specific requirements.  
 ■ Caution: Applications involving reciprocating engines and reciprocating driven devices are subject to critical rotational speeds which may damage the coupling and/or connected equipment. Contact Lovejoy Application Engineering with specific requirements.

## Grid Coupling Selection Worksheet


Customer Name: \_\_\_\_\_ Contact Name: \_\_\_\_\_

Phone Number: \_\_\_\_\_ Email Address: \_\_\_\_\_

### Standard Grid Style Coupling



### Standard Grid Spacer Coupling



#### 1. Type of Driver (Electric Motor, Combustion Engine, Gearbox, etc.) :

For combustion engines, define type

Gasoline, Diesel, Natural Gas, etc.: \_\_\_\_\_ Number of cylinders: \_\_\_\_\_

#### 2. Driver Horse Power : \_\_\_\_\_ 3. Driver or Gearbox output RPM: \_\_\_\_\_

Retrieve the application Service Factor from Page GD-7 and GD-8 : \_\_\_\_\_ then  
calculate the Selection Torque using the following formula:

$$\text{Torque (in-lbs)} = \frac{\text{HP} \times 63025}{\text{RPM}} \times \text{Service Factor} = \text{Selection Torque} = \text{_____ in-lbs}$$

#### 4. Driver Shaft Diameter : \_\_\_\_\_ Keyway size : KW Width \_\_\_\_\_ KW Height \_\_\_\_\_

By default, sizes 1020 thru 1090 have Clearance fits; Sizes 1100 thru 1200 have Interference Fits  
If requesting other than default, please specify Clearance Fit, Interference Fit, Metric (P7, H7, etc)

#### 5. Driver Usable Shaft Length : \_\_\_\_\_ (Measure from the end of the shaft to any obstruction)

#### 6. Distance between shaft ends (BSE) : \_\_\_\_\_ (Stock BSE values can be found on page GD-14)

#### 7. Type of Driven Equipment: \_\_\_\_\_


#### 8. Driven Shaft Diameter : \_\_\_\_\_ Keyway size : KW Width \_\_\_\_\_ KW Height \_\_\_\_\_

By default, sizes 1020 thru 1090 have Clearance fits; Sizes 1100 thru 1200 have Interference Fits  
If requesting other than default, please specify Clearance Fit, Interference Fit, Metric (P7, H7, etc)

#### 9. Driven Usable Shaft Length : \_\_\_\_\_ (Measure from the end of the shaft to any obstruction)

#### 10. Total Mounting Length : \_\_\_\_\_ (Advise of any obstructions, walls, beams, guards, pipes, etc.)

#### 11. For taper bores or splines, please contact Lovejoy Application Engineering or Product Manager.



**For additional bore and keyway  
information, see the Engineering  
Data Section of the Power  
Transmission Products Catalog**

GD

**Lovejoy, Inc.**  
**World Headquarters**  
2655 Wisconsin Avenue  
Downers Grove, IL 60515

**Send this form to:**  
appleng@lovejoy-inc.com  
or fax to: 800-446-0878

## Standard Grid Style Couplings Horizontal and Vertical Cover

The Lovejoy Grid coupling is an ideal coupling for applications where excellent performance is desired and additional requirements for vibration dampening may exist. The Horizontal Split Cover design is recommended in applications where there may be some constraints on the diameter of the coupling. The vertical design is recommended for applications where higher speed is one of the requirements.

### Features:

- Designed for ease of maintenance and grid spring replacement
- High tensile grid springs ensure superior coupling performance and longer coupling life
- Split covers allow for easy access to grid springs
- Interchangeable with industry standard grid couplings



Horizontal Cover Style



Vertical Cover Style


### Grid Coupling Performance Data

| Size | Nominal<br>Torque <sup>1</sup><br><br>in-lbs      Nm |         | Maximum<br>Speed<br><br>Horizontal      Vertical<br>RPM              RPM |            | ID1 - ID2                  |     |                            |     | SL <sup>2</sup>                                  | T  | Weight<br>Solid<br><br>lbs      kg |        | Moment of Inertia |          |
|------|--|---------|--|------------|----------------------------|-----|----------------------------|-----|--|--|------------------------------------|--------|-------------------|----------|
|      |  |         |  |            | Min Bore<br><br>in      mm |     | Max Bore<br><br>in      mm |     | Set Screw  |  |                                    |        | Solid Hubs        |          |
|      |  |         | Location<br>in   | Size<br>in |                            |     |                            |     | Horizontal<br>WR <sup>2</sup> lb-in <sup>2</sup> | Vertical<br>WR <sup>2</sup> lb-in <sup>2</sup> |                                    |        |                   |          |
| 1020 | 460  | 52      | 4,500  | 6,000      | 0.500                      | 12  | 1.125                      | 28  | 0.50   | #8-32  | 4.3                                | 2.0    | 4.83              | 5.32     |
| 1030 | 1,320  | 149     | 4,500  | 6,000      | 0.500                      | 12  | 1.375                      | 35  | 0.31   | #8-32  | 5.7                                | 2.6    | 7.61              | 7.99     |
| 1040 | 2,200  | 249     | 4,500  | 6,000      | 0.500                      | 12  | 1.625                      | 42  | 0.44   | #10-24   | 7.4                                | 3.4    | 11.19             | 11.99    |
| 1050 | 3,850  | 435     | 4,500  | 6,000      | 0.500                      | 12  | 1.875                      | 48  | 0.62   | #10-24   | 12.0                               | 5.4    | 24.85             | 25.76    |
| 1060 | 6,050  | 983     | 4,350  | 6,000      | 0.750                      | 19  | 2.125                      | 54  | 0.44   | #10-24   | 16.0                               | 7.3    | 40.66             | 41.16    |
| 1070 | 8,800  | 994     | 4,125  | 5,500      | 0.750                      | 19  | 2.500                      | 64  | 0.88   | 1/4-20   | 23.0                               | 10.4   | 63.18             | 61.68    |
| 1080 | 18,150   | 2 051   | 3,600  | 4,750      | 1.062                      | 27  | 3.000                      | 76  | 0.94   | 1/4-20   | 39.0                               | 17.7   | 154.00            | 148.00   |
| 1090 | 33,000   | 3 728   | 3,600  | 4,000      | 1.062                      | 27  | 3.500                      | 89  | 1.03   | 5/16-18  | 56.0                               | 25.4   | 269.00            | 272.00   |
| 1100 | 55,550   | 6 276   | 2,400  | 3,250      | 1.625                      | 41  | 4.000                      | 102 | —  | —  | 93.0                               | 42.2   | 609.00            | 608.00   |
| 1110 | 82,500   | 9 321   | 2,250  | 3,000      | 1.625                      | 41  | 4.500                      | 117 | —  | —  | 120.0                              | 54.4   | 923.00            | 930.00   |
| 1120 | 121,000  | 13 671  | 2,025  | 2,700      | 2.375                      | 60  | 5.000                      | 127 | —  | —  | 180.0                              | 81.2   | 1,755.00          | 1,611.00 |
| 1130 | 176,000  | 19 884  | 1,800  | 2,400      | 2.625                      | 67  | 6.000                      | 152 | —  | —  | 270.0                              | 121.0  | 3,375.00          | 3,568.00 |
| 1140 | 253,000  | 28 584  | 1,650  | 2,200      | 2.625                      | 67  | 7.250                      | 184 | —  | —  | 394.0                              | 177.8  | 6,306.00          | 6,431.00 |
| 1150 | 352,000  | 39 769  | 1,500  | —          | 4.250                      | 108 | 8.000                      | 200 | —  | —  | 523.0                              | 237.2  | —                 | —        |
| 1160 | 495,000  | 55 925  | 1,350  | —          | 4.750                      | 121 | 9.000                      | 228 | —  | —  | 720.0                              | 326.5  | —                 | —        |
| 1170 | 660,000  | 74 567  | 1,225  | —          | 5.250                      | 134 | 10.000                     | 254 | —  | —  | 1,022.5                            | 463.7  | —                 | —        |
| 1180 | 915,200  | 103 399 | 1,100  | —          | 6.000                      | 153 | 11.000                     | 280 | —  | —  | 1,341.7                            | 608.5  | —                 | —        |
| 1190 | 1,210,000  | 136 706 | 1,050  | —          | 6.000                      | 153 | 12.000                     | 305 | —  | —  | 1,710.0                            | 775.5  | —                 | —        |
| 1200 | 1,650,000  | 186 417 | 900  | —          | 7.000                      | 178 | 13.000                     | 330 | —  | —  | 2,331.0                            | 1057.1 | —                 | —        |

Notes: ■ 1 Indicates: Peak torque is typically twice the Nominal Torque value.


■ 2 Indicates: Sizes 1020 thru 1090 are bored with clearance fit with 2 set screws at 90°, sizes 1100 and larger are bored with interference fit and no set screw.

Grid Coupling with Horizontal Style Cover




Sizes 1020 - 1140

Grid Coupling with Vertical Style Cover



Sizes 1150 - 1200



Sizes 1020 - 1090

### Grid Coupling Dimensional Data

| Size | OAL   |       | R    | L             |               | FL   | G 1   |      | LTB   |       | OD            |               |       |       | FD    |       | HD    |       |
|------|-------|-------|------|---------------|---------------|------|-------|------|-------|-------|---------------|---------------|-------|-------|-------|-------|-------|-------|
|      | in    | mm    |      | Horz<br>Cover | Vert<br>Cover |      | in    | mm   | in    | mm    | Horz<br>Cover | Vert<br>Cover | in    | mm    | in    | mm    | in    | mm    |
| 1020 | 3.88  | 98.5  | 1.88 | 2.62          | 0.96          | 0.38 | 0.118 | 3.00 | 1.87  | 47.5  | 4.00          | 101.6         | 4.38  | 111.3 | 2.50  | 63.5  | 1.56  | 39.7  |
| 1030 | 3.88  | 98.5  | 1.88 | 2.69          | 1.00          | 0.38 | 0.118 | 3.00 | 1.87  | 47.5  | 4.33          | 110.0         | 4.75  | 120.7 | 2.88  | 73.0  | 1.94  | 49.2  |
| 1040 | 4.12  | 104.7 | 2.00 | 2.75          | 1.03          | 0.38 | 0.118 | 3.00 | 2.00  | 50.8  | 4.63          | 117.6         | 5.06  | 128.5 | 3.25  | 82.6  | 2.25  | 57.2  |
| 1050 | 4.88  | 123.8 | 2.38 | 3.18          | 1.24          | 0.47 | 0.118 | 3.00 | 2.37  | 60.3  | 5.43          | 138.0         | 5.81  | 147.6 | 3.88  | 98.4  | 2.63  | 66.7  |
| 1060 | 5.12  | 130.0 | 2.50 | 3.68          | 1.27          | 0.50 | 0.118 | 3.00 | 2.50  | 63.5  | 5.93          | 150.5         | 6.38  | 162.1 | 4.38  | 111.1 | 3.00  | 76.2  |
| 1070 | 6.12  | 155.5 | 2.63 | 3.80          | 1.33          | 0.50 | 0.118 | 3.00 | 3.00  | 76.2  | 6.37          | 161.8         | 6.81  | 173.0 | 4.88  | 123.8 | 3.44  | 87.3  |
| 1080 | 7.12  | 180.8 | 3.50 | 4.55          | 1.74          | 0.50 | 0.118 | 3.00 | 3.50  | 88.9  | 7.64          | 194.0         | 7.13  | 181.1 | 5.00  | 127.0 | 4.13  | 104.9 |
| 1090 | 7.88  | 200.0 | 3.75 | 4.80          | 1.86          | 0.50 | 0.118 | 3.00 | 3.87  | 98.4  | 8.39          | 213.0         | 7.88  | 200.2 | 5.88  | 149.2 | 4.87  | 123.7 |
| 1100 | 9.69  | 246.1 | 4.75 | 6.12          | 2.38          | 0.63 | 0.177 | 4.50 | 4.75  | 120.6 | 9.84          | 250.0         | 9.69  | 246.1 | 7.75  | 196.9 | 5.59  | 142.0 |
| 1110 | 10.19 | 258.7 | 4.88 | 6.36          | 2.50          | 0.63 | 0.177 | 4.50 | 5.00  | 127.0 | 10.63         | 270.0         | 11.25 | 285.8 | 8.50  | 215.9 | 6.31  | 160.3 |
| 1120 | 12.00 | 304.8 | 5.63 | 7.54          | 2.94          | 0.68 | 0.236 | 6.00 | 5.87  | 149.2 | 12.13         | 308.0         | 12.56 | 319.0 | 9.63  | 244.5 | 7.06  | 179.4 |
| 1130 | 13.00 | 330.2 | 5.75 | 7.68          | 3.00          | 0.82 | 0.236 | 6.00 | 6.37  | 161.9 | 13.62         | 346.0         | 14.88 | 378.0 | 11.13 | 282.6 | 8.56  | 217.5 |
| 1140 | 14.63 | 371.6 | 6.13 | 7.91          | 3.13          | 0.82 | 0.236 | 6.00 | 7.20  | 182.9 | 15.12         | 384.0         | 16.38 | 416.1 | 12.63 | 320.7 | 10.00 | 254.0 |
| 1150 | 14.65 | 372.1 | —    | 10.69         | —             | —    | 0.236 | 6.00 | 7.20  | 182.9 | 17.84         | 453.1         | —     | —     | —     | —     | 10.60 | 269.2 |
| 1160 | 15.85 | 402.6 | —    | 10.96         | —             | —    | 0.236 | 6.00 | 7.80  | 198.1 | 19.74         | 501.4         | —     | —     | —     | —     | 12.00 | 304.8 |
| 1170 | 17.25 | 437.1 | —    | 12.10         | —             | —    | 0.236 | 6.00 | 8.50  | 215.9 | 22.30         | 566.4         | —     | —     | —     | —     | 14.00 | 355.6 |
| 1180 | 19.05 | 483.9 | —    | 12.64         | —             | —    | 0.236 | 6.00 | 9.40  | 238.8 | 24.80         | 629.9         | —     | —     | —     | —     | 15.50 | 393.7 |
| 1190 | 20.65 | 524.5 | —    | 12.80         | —             | —    | 0.236 | 6.00 | 10.20 | 259.1 | 26.60         | 675.6         | —     | —     | —     | —     | 17.20 | 436.9 |
| 1200 | 22.25 | 565.1 | —    | 14.00         | —             | —    | 0.236 | 6.00 | 10.98 | 279.0 | 29.80         | 756.9         | —     | —     | —     | —     | 19.60 | 497.8 |

Note: ■ 1 indicates: For sizes 1020 thru 1080, the gap tolerance for dimension G is + .050" / - .050" (+ 1.5 mm / - 1.5 mm).  
 For sizes 1090 thru 1120, the gap tolerance for dimension G is + .177" / - .118" (+ 4.5 mm / - 3 mm).  
 For sizes 1120 thru 1200, the gap tolerance for dimension G is + .236" / - .177" (+ 6 mm / - 4.5 mm).

### Standard Grid Spacer and Half Spacer Style Couplings Horizontal Cover

The Lovejoy Grid Spacer coupling is an ideal coupling for applications where there is a requirement for some vibration dampening in installations that are not close coupled. This means some amount of gap, or BSE exists between the driver and driven equipment shafts.

All Lovejoy Grid Spacer Couplings are supplied with Horizontal Split Covers. The split cover design allows for quick access to the grid spring for ease of maintenance or grid spring replacement. The Horizontal Split Cover is also ideal for applications where there may be some constraints on the diameter of the coupling.

#### Features:

- Designed for ease of maintenance and grid spring replacement
- High tensile grid springs ensure superior coupling performance and longer coupling life
- Split covers allow for easy access to grid springs
- Interchangeable with industry standard grid couplings



Full Spacer Style



Half Spacer Style

### Grid Series Spacer Coupling Performance and Dimensional Data

| Size | Nominal<br>Torque <sup>1</sup> |            | Maximum<br>Speed<br>RPM | ID1 - ID2         |                   |     | G<br>in | G1<br>in | LTB<br>Std<br>Hub<br>in mm |    | FD<br>in | HD<br>in | OD<br>in | SL        | T       |
|------|--------------------------------|------------|-------------------------|-------------------|-------------------|-----|---------|----------|----------------------------|----|----------|----------|----------|-----------|---------|
|      |                                |            |                         | Min Bore<br>in/mm | Max Bore<br>in mm |     |         |          |                            |    |          |          |          | Set Screw |         |
|      | Location<br>in                 | Size<br>in |                         |                   |                   |     |         |          |                            |    |          |          |          |           |         |
| 1020 | 460                            | 48         | 3,600                   | Solid             | 1.38              | 35  | 0.19    | 0.03     | 1.87                       | 47 | 3.38     | 2.06     | 4.00     | 0.50      | #8-32   |
| 1030 | 1,320                          | 136        | 3,600                   | Solid             | 1.63              | 41  | 0.19    | 0.03     | 1.87                       | 47 | 3.69     | 2.34     | 4.38     | 0.31      | #8-32   |
| 1040 | 2,200                          | 226        | 3,600                   | Solid             | 2.13              | 54  | 0.19    | 0.03     | 2.00                       | 51 | 4.44     | 3.09     | 4.62     | 0.44      | #10-24  |
| 1050 | 3,850                          | 395        | 3,600                   | Solid             | 2.38              | 60  | 0.19    | 0.03     | 2.37                       | 60 | 4.94     | 3.44     | 5.44     | 0.62      | #10-24  |
| 1060 | 6,050                          | 621        | 3,600                   | Solid             | 2.88              | 73  | 0.19    | 0.06     | 2.50                       | 64 | 5.69     | 4.06     | 5.94     | 0.44      | #10-24  |
| 1070 | 8,800                          | 904        | 3,600                   | Solid             | 3.13              | 79  | 0.19    | 0.06     | 3.00                       | 76 | 6.00     | 4.31     | 6.38     | 0.88      | 1/4-20  |
| 1080 | 18,150                         | 1 864      | 3,600                   | Solid             | 3.50              | 89  | 0.19    | 0.06     | 3.50                       | 89 | 7.00     | 4.81     | 7.62     | 0.94      | 1/4-20  |
| 1090 | 33,000                         | 3 390      | 3,600                   | Solid             | 4.00              | 102 | 0.19    | 0.06     | 3.87                       | 98 | 8.25     | 5.62     | 8.38     | 1.03      | 5/16-18 |


Note: ■ 1 Indicates: Peak torque is typically twice the Nominal Torque value.

To calculate the OAL (Over All Length) for Full Spacer Style (Spacer Hubs both ends) use the following formula:


$$OAL = (2 \times LTB) + (2 \times S) + (2 \times G1) + G$$

To calculate the OAL (Over All Length) for Half Spacer Style (Spacer Hubs one end only) use the following formula:

$$OAL = LTB + LTB2 + S + G1 + G$$



**Half Spacer Style Grid Coupling**



**Full Spacer Style Grid Coupling**

Each column has a header showing the desired shaft separation (BSE). By extending the coupling size over to the desired column for the shaft separation, the box lists the two hub sizes required to achieve the BSE.

**Grid Series Half Spacer Dimensional Data**

| Size | Spacer Hubs<br><br>1-side only | BSE - Application Shaft Separation |       |       |       |       |
|------|--------------------------------|------------------------------------|-------|-------|-------|-------|
|      |                                | 1.781                              | 2.219 | 2.531 | 3.500 | 3.656 |
|      |                                | Spacer Hub Lengths S-Dimension     |       |       |       |       |
| 1020 | Std Hub                        | Std                                | Std   | Std   | —     | —     |
|      | Hub 2                          | 1.625                              | 2.062 | 2.375 | —     | —     |
| 1030 | Std Hub                        | Std                                | Std   | Std   | Std   | Std   |
|      | Hub 2                          | 1.625                              | 2.062 | 2.375 | 3.344 | 3.500 |
| 1040 | Std Hub                        | Std                                | Std   | Std   | Std   | Std   |
|      | Hub 2                          | 1.625                              | 2.062 | 2.375 | 3.344 | 3.500 |
| 1050 | Std Hub                        | —                                  | —     | Std   | —     | Std   |
|      | Hub 2                          | —                                  | —     | 2.375 | —     | 3.500 |
| 1060 | Std Hub                        | —                                  | —     | Std   | —     | Std   |
|      | Hub 2                          | —                                  | —     | 2.344 | —     | 3.469 |
| 1070 | Std Hub                        | —                                  | —     | Std   | —     | Std   |
|      | Hub 2                          | —                                  | —     | 2.344 | —     | 3.469 |
| 1080 | Std Hub                        | —                                  | —     | —     | —     | Std   |
|      | Hub 2                          | —                                  | —     | —     | —     | 3.469 |
| 1090 | Std Hub                        | —                                  | —     | —     | —     | Std   |
|      | Hub 2                          | —                                  | —     | —     | —     | 3.469 |

GD

**Grid Series Full Spacer Dimensional Data**


| Size | Spacer Hubs<br><br>Both Hubs | BSE - Application Shaft Separation                   |       |       |       |       |       |       |       |       |       |       |       |       |       |       |
|------|------------------------------|--|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|
|      |                              | 3.500  | 3.980 | 4.250 | 4.375 | 4.688 | 5.000 | 5.219 | 5.375 | 5.656 | 5.813 | 5.969 | 6.125 | 6.938 | 7.094 | 7.250 |
|      |                              | Spacer Hub Lengths S - Dimension (See drawing above) |       |       |       |       |       |       |       |       |       |       |       |       |       |       |
| 1020 | Hub 1                        | 1.625  | 1.625 | 1.625 | 2.062 | 2.062 | 2.375 | —     | —     | —     | —     | —     | —     | —     | —     | —     |
|      | Hub 2                        | 1.625  | 2.062 | 2.375 | 2.062 | 2.375 | 2.375 | —     | —     | —     | —     | —     | —     | —     | —     | —     |
| 1030 | Hub 1                        | 1.625  | 1.625 | 1.625 | 2.062 | 2.062 | 2.375 | —     | 1.625 | —     | 2.062 | 2.375 | 2.375 | —     | —     | 3.500 |
|      | Hub 2                        | 1.625  | 2.062 | 2.375 | 2.062 | 2.375 | 2.375 | —     | 3.500 | —     | 3.500 | 3.344 | 3.500 | —     | —     | 3.500 |
| 1040 | Hub 1                        | 1.625  | 1.625 | 1.625 | 2.062 | 2.062 | 2.375 | 1.625 | 1.625 | 2.062 | 2.062 | 2.375 | 2.375 | 3.344 | 3.344 | 3.500 |
|      | Hub 2                        | 1.625  | 2.062 | 2.375 | 2.062 | 2.375 | 2.375 | 3.344 | 3.500 | 3.344 | 3.500 | 3.344 | 3.500 | 3.344 | 3.500 | 3.500 |
| 1050 | Hub 1                        | —  | —     | —     | 2.062 | 2.062 | 2.375 | —     | —     | 2.062 | 2.062 | —     | 2.375 | 3.344 | 3.344 | 3.500 |
|      | Hub 2                        | —  | —     | —     | 2.062 | 2.375 | 2.375 | —     | —     | 3.344 | 3.500 | —     | 3.500 | 3.344 | 3.500 | 3.500 |
| 1060 | Hub 1                        | —  | —     | —     | —     | —     | 2.344 | —     | —     | —     | —     | —     | 2.344 | —     | —     | 3.469 |
|      | Hub 2                        | —  | —     | —     | —     | —     | 2.344 | —     | —     | —     | —     | —     | 3.469 | —     | —     | 3.469 |
| 1070 | Hub 1                        | —  | —     | —     | —     | —     | 2.344 | —     | —     | —     | —     | —     | 2.344 | —     | —     | 3.469 |
|      | Hub 2                        | —  | —     | —     | —     | —     | 2.344 | —     | —     | —     | —     | —     | 3.469 | —     | —     | 3.469 |
| 1080 | Hub 1                        | —  | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 3.469 |
|      | Hub 2                        | —  | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 3.469 |
| 1090 | Hub 1                        | —  | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 3.469 |
|      | Hub 2                        | —  | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 3.469 |

#### Grid Series Misalignment Capacity (Standard and Spacer Type)


| Size | P                    | X - Y           | P              | X-Y             | G             |
|------|----------------------|-----------------|----------------|-----------------|---------------|
|      | Maximum Misalignment |                 |                |                 | Nominal       |
|      | Installation         |                 | Operational    |                 | BSE - Gap     |
|      | Parallel<br>in       | Angular 1<br>in | Parallel<br>in | Angular 1<br>in | +/- 10%<br>in |
| 1020 | 0.006                | 0.002           | 0.012          | 0.009           | 0.118         |
| 1030 | 0.006                | 0.003           | 0.012          | 0.011           | 0.118         |
| 1040 | 0.006                | 0.003           | 0.012          | 0.013           | 0.118         |
| 1050 | 0.008                | 0.004           | 0.016          | 0.015           | 0.118         |
| 1060 | 0.008                | 0.004           | 0.016          | 0.018           | 0.118         |
| 1070 | 0.008                | 0.005           | 0.016          | 0.020           | 0.118         |
| 1080 | 0.008                | 0.006           | 0.016          | 0.024           | 0.118         |
| 1090 | 0.008                | 0.007           | 0.016          | 0.028           | 0.118         |
| 1100 | 0.010                | 0.008           | 0.020          | 0.032           | 0.177         |
| 1110 | 0.010                | 0.009           | 0.020          | 0.035           | 0.177         |
| 1120 | 0.011                | 0.010           | 0.022          | 0.040           | 0.236         |
| 1130 | 0.011                | 0.012           | 0.022          | 0.047           | 0.236         |
| 1140 | 0.011                | 0.013           | 0.022          | 0.053           | 0.236         |
| 1150 | 0.012                | 0.015           | 0.024          | 0.061           | 0.236         |
| 1160 | 0.012                | 0.017           | 0.024          | 0.070           | 0.236         |
| 1170 | 0.012                | 0.020           | 0.024          | 0.079           | 0.236         |
| 1180 | 0.015                | 0.022           | 0.030          | 0.089           | 0.236         |
| 1190 | 0.015                | 0.024           | 0.030          | 0.096           | 0.236         |
| 1200 | 0.015                | 0.027           | 0.030          | 0.107           | 0.236         |

Note: ■ 1 Indicates: Allowable angular misalignment at installation is 1/16°.  
 Allowable angular misalignment during operation is 1/4°.


#### Misalignment Capability:




**Parallel:** The movement of the grid in the hub grooves accommodates parallel misalignment and still permits full functioning of the grid-groove action in damping out shock and vibration.




**Angular:** Under angular misalignment, the grid-groove design permits a rocking and sliding action of the grid and hubs without any loss of power through the resilient grid.




**Axial:** End float is permitted for both driving and driven members because the grid slides freely in the grooves.



Normal Gap



Parallel Misalignment



Angular Misalignment



# Grid

## Industry Standard Interchange Chart

### Item Selection

### Industry Standard Interchange

Lovejoy Grid couplings are interchangeable with industry standard grid couplings supplied by other major coupling manufacturers. The chart below provides part numbers necessary to make the crossover from these other major manufacturers.

### Industry Standard Grid Coupling Interchange Chart

| Lovejoy®<br>Size | Horizontal — Split Cover |                               |                      |                        | Vertical — Split Cover |                               |                      |                        |
|------------------|--------------------------|-------------------------------|----------------------|------------------------|------------------------|-------------------------------|----------------------|------------------------|
|                  | Falk®<br>Steelflex®      | Morse/Browning®<br>Grid-Flex® | Dodge®<br>Grid-Lign® | Kop-Flex®<br>Kop-Grid® | Falk®<br>Steelflex®    | Morse/Browning®<br>Grid-Flex® | Dodge®<br>Grid-Lign® | Kop-Flex®<br>Kop-Grid® |
| 1020             | 1020T10                  | GF2020H                       | 1020T10              | 1020H                  | 1020T20                | GF2020V                       | 1020T20              | 1020V                  |
| 1030             | 1030T10                  | GF2030H                       | 1030T10              | 1030H                  | 1030T20                | GF2030V                       | 1030T20              | 1030V                  |
| 1040             | 1040T10                  | GF2040H                       | 1040T10              | 1040H                  | 1040T20                | GF2040V                       | 1040T20              | 1040V                  |
| 1050             | 1050T10                  | GF2050H                       | 1050T10              | 1050H                  | 1050T20                | GF2050V                       | 1050T20              | 1050V                  |
| 1060             | 1060T10                  | GF2060H                       | 1060T10              | 1060H                  | 1060T20                | GF2060V                       | 1060T20              | 1060V                  |
| 1070             | 1070T10                  | GF2070H                       | 1070T10              | 1070H                  | 1070T20                | GF2070V                       | 1070T20              | 1070V                  |
| 1080             | 1080T10                  | GF2080H                       | 1080T10              | 1080H                  | 1080T20                | GF2080V                       | 1080T20              | 1080V                  |
| 1090             | 1090T10                  | GF2090H                       | 1090T10              | 1090H                  | 1090T20                | GF2090V                       | 1090T20              | 1090V                  |
| 1100             | 1100T10                  | GF2100H                       | 1100T10              | 1100H                  | 1100T20                | GF2100V                       | 1100T20              | 1100V                  |
| 1110             | 1110T10                  | GF2110H                       | 1110T10              | 1110H                  | 1110T20                | GF2110V                       | 1110T20              | 1110V                  |
| 1120             | 1120T10                  | GF2120H                       | 1120T10              | 1120H                  | 1120T20                | GF2120V                       | 1120T20              | 1120V                  |
| 1130             | 1130T10                  | GF2130H                       | 1130T10              | 1130H                  | 1130T20                | GF2130V                       | 1130T20              | 1130V                  |
| 1140             | 1140T10                  | GF2140H                       | 1140T10              | 1140H                  | 1140T20                | GF2140V                       | 1140T20              | 1140V                  |
| 1150             | 1150T10                  | —                             | —                    | —                      | —                      | —                             | —                    | —                      |
| 1160             | 1160T10                  | —                             | —                    | —                      | —                      | —                             | —                    | —                      |
| 1170             | 1170T10                  | —                             | —                    | —                      | —                      | —                             | —                    | —                      |
| 1180             | 1180T10                  | —                             | —                    | —                      | —                      | —                             | —                    | —                      |
| 1190             | 1190T10                  | —                             | —                    | —                      | —                      | —                             | —                    | —                      |
| 1200             | 1200T10                  | —                             | —                    | —                      | —                      | —                             | —                    | —                      |

GD



# Grid

## Grid Coupling Hubs – Inch Bore / Keyway

### Item Selection

**Grid Coupling Hubs - Inch Bore and Keyway UPC Number Selection Table**

| Bore         | Keyway      | 1020  | 1030  | 1040  | 1050  | 1060  | 1070  | 1080  | 1090  | 1100  | 1110  | 1120  | 1130  | 1140  |
|--------------|-------------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|
| <b>SOLID</b> |             | 05231 | 05232 | 05233 | 05234 | 05235 | 05236 | 05237 | 05238 | 05239 | 05240 | 05241 | 05242 | 05243 |
| 1/2          | 1/8 x 1/16  | 05458 | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     |
| 5/8          | 3/16 x 3/32 | 05459 | 05464 | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     |
| 3/4          | 3/16 x 3/32 | 05460 | 05465 | 06140 | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     |
| 7/8          | 3/16 x 3/32 | 05461 | 05466 | 05471 | 06141 | 06142 | 99245 | —     | —     | —     | —     | —     | —     | —     |
| 15/16        | 1/4 x 1/8   | 06100 | 06101 | 06103 | 06106 | 16752 | —     | —     | —     | —     | —     | —     | —     | —     |
| 1            | 1/4 x 1/8   | 05462 | 05467 | 05472 | 06107 | 06112 | 90793 | —     | —     | —     | —     | —     | —     | —     |
| 1-1/8        | 1/4 x 1/8   | 05463 | 05468 | 05473 | 05478 | 06113 | 06144 | 07364 | —     | —     | —     | —     | —     | —     |
| 1-3/16       | 1/4 x 1/8   | —     | 06102 | 06104 | 06108 | 06114 | —     | —     | —     | —     | —     | —     | —     | —     |
| 1-1/4        | 1/4 x 1/8   | —     | 05469 | 05474 | 05479 | 06115 | 06145 | 06148 | —     | —     | —     | —     | —     | —     |
| 1-3/8        | 5/16 x 5/32 | —     | 05470 | 05475 | 05480 | 05485 | 06119 | 06149 | —     | —     | —     | —     | —     | —     |
| 1-7/16       | 3/8 x 3/16  | —     | —     | 06105 | 06109 | 06116 | 06120 | 08124 | —     | —     | —     | —     | —     | —     |
| 1-1/2        | 3/8 x 3/16  | —     | —     | 05476 | 05481 | 05486 | 06121 | 91199 | —     | —     | —     | —     | —     | —     |
| 1-5/8        | 3/8 x 3/16  | —     | —     | 05477 | 05482 | 05487 | 05492 | 06150 | —     | —     | —     | —     | —     | —     |
| 1-11/16      | 3/8 x 3/16  | —     | —     | —     | 06110 | 06117 | 06122 | 97351 | —     | —     | —     | —     | —     | —     |
| 1-3/4        | 3/8 x 3/16  | —     | —     | —     | 05483 | 05488 | 05493 | 06124 | 94087 | —     | —     | —     | —     | —     |
| 1-13/16      | 1/2 x 1/4   | —     | —     | —     | 06111 | 06118 | 06123 | 06125 | —     | —     | —     | —     | —     | —     |
| 1-7/8        | 1/2 x 1/4   | —     | —     | —     | 05484 | 05489 | 05494 | 06126 | 06154 | —     | —     | —     | —     | —     |
| 1-15/16      | 1/2 x 1/4   | —     | —     | —     | —     | 06143 | 06146 | 06151 | 16852 | —     | —     | —     | —     | —     |
| 2            | 1/2 x 1/4   | —     | —     | —     | —     | 05490 | 05495 | 05500 | 06155 | —     | —     | —     | —     | —     |
| 2-1/8        | 1/2 x 1/4   | —     | —     | —     | —     | 05491 | 05496 | 05501 | 06127 | —     | —     | —     | —     | —     |
| 2-3/16       | 1/2 x 1/4   | —     | —     | —     | —     | —     | 06147 | 06152 | 06156 | —     | —     | —     | —     | —     |
| 2-1/4        | 1/2 x 1/4   | —     | —     | —     | —     | —     | 05497 | 05502 | 06128 | 11767 | —     | —     | —     | —     |
| 2-3/8        | 5/8 x 5/16  | —     | —     | —     | —     | —     | 05498 | 05503 | 06129 | 09399 | —     | —     | —     | —     |
| 2-1/2        | 5/8 x 5/16  | —     | —     | —     | —     | —     | 05499 | 05504 | 05509 | 05519 | —     | —     | —     | —     |
| 2-5/8        | 5/8 x 5/16  | —     | —     | —     | —     | —     | —     | 05505 | 05510 | 05520 | —     | —     | —     | —     |
| 2-3/4        | 5/8 x 5/16  | —     | —     | —     | —     | —     | —     | 05506 | 05511 | 05521 | —     | —     | —     | —     |
| 2-7/8        | 3/4 x 3/8   | —     | —     | —     | —     | —     | —     | 05507 | 05512 | 05522 | —     | —     | —     | —     |
| 2-15/16      | 3/4 x 3/8   | —     | —     | —     | —     | —     | —     | 06153 | 04386 | —     | —     | —     | —     | —     |
| 3            | 3/4 x 3/8   | —     | —     | —     | —     | —     | —     | 05508 | 05513 | 05523 | 05532 | 05542 | —     | —     |
| 3-1/8        | 3/4 x 3/8   | —     | —     | —     | —     | —     | —     | —     | 05514 | 05524 | 05533 | 05543 | —     | —     |
| 3-1/4        | 3/4 x 3/8   | —     | —     | —     | —     | —     | —     | —     | 05515 | 05525 | 05534 | 05544 | —     | —     |
| 3-3/8        | 7/8 x 7/16  | —     | —     | —     | —     | —     | —     | —     | 05516 | 05526 | 05535 | 05545 | —     | —     |
| 3-7/16       | 7/8 x 7/16  | —     | —     | —     | —     | —     | —     | —     | 06158 | 95492 | —     | —     | —     | —     |
| 3-1/2        | 7/8 x 7/16  | —     | —     | —     | —     | —     | —     | —     | 05517 | 05527 | 05536 | 05546 | 05553 | —     |
| 3-5/8        | 7/8 x 7/16  | —     | —     | —     | —     | —     | —     | —     | —     | 05528 | 05537 | 05547 | 05554 | —     |
| 3-3/4        | 7/8 x 7/16  | —     | —     | —     | —     | —     | —     | —     | —     | 05529 | 05538 | 05548 | 05555 | —     |
| 3-7/8        | 1 x 1/2     | —     | —     | —     | —     | —     | —     | —     | —     | 05530 | 05539 | 05549 | 05556 | 05562 |
| 4            | 1 x 1/2     | —     | —     | —     | —     | —     | —     | —     | —     | 05531 | 05540 | 05550 | 05557 | 05563 |
| 4-1/2        | 1 x 1/2     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 05541 | 05551 | 05558 | 05564 |
| 5            | 1 1/4 x 5/8 | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 05552 | 05559 | 05565 |
| 5-1/2        | 1 1/4 x 5/8 | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 05560 | 05566 |
| 6            | 1 1/2 x 3/4 | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 05561 | 05567 |
| 6-1/2        | 1 1/2 x 3/4 | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 05568 |
| 7            | 1 1/2 x 3/4 | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | —     | 05569 |

- Notes:
- Size 1020 thru 1090 hubs are provided with clearance fit bores and 2 set screws at 90°.
  - Size 1100 thru 1200 hubs are provided with interference fit bores and no set screws.
  - Lovejoy machines Inch bores and keyways to meet tolerances define in the ANSI/AGMA 9002-B04 Standard.
  - When referencing the Lovejoy UPC number from this table, include 697904 as a prefix to the number shown.



# Grid

## Grid Coupling Hubs – Metric Bore / Keyway


### Item Selection

**Grid Coupling Hubs - Metric Bore and Keyway UPC Number Selection Table**

| Bore | Keyway   | 1020  | 1030  | 1040  | 1050  | 1060  | 1070  | 1080  | 1090  |
|------|----------|-------|-------|-------|-------|-------|-------|-------|-------|
| 14   | 5 x 2.3  | 05780 | —     | —     | —     | —     | —     | —     | —     |
| 15   | 5 x 2.3  | 05781 | —     | —     | —     | —     | —     | —     | —     |
| 16   | 5 x 2.3  | 05782 | 07703 | —     | —     | —     | —     | —     | —     |
| 19   | 6 x 2.8  | 05783 | 05788 | —     | —     | —     | —     | —     | —     |
| 20   | 6 x 2.8  | 05784 | 05789 | 90454 | —     | —     | —     | —     | —     |
| 22   | 6 x 2.8  | 05785 | 05790 | 93740 | —     | —     | —     | —     | —     |
| 24   | 8 x 3.3  | 05786 | 05791 | 05797 | 19975 | —     | —     | —     | —     |
| 25   | 8 x 3.3  | 05787 | 05792 | 05798 | 16296 | —     | —     | —     | —     |
| 28   | 8 x 3.3  | —     | 05793 | 05799 | 05805 | —     | —     | —     | —     |
| 30   | 8 x 3.3  | —     | 05794 | 05800 | 05806 | —     | —     | —     | —     |
| 32   | 10 x 3.3 | —     | 05795 | 05801 | 05807 | 11865 | —     | —     | —     |
| 35   | 10 x 3.3 | —     | 05796 | 05802 | 05808 | 05812 | 05817 | —     | —     |
| 38   | 10 x 3.3 | —     | —     | 05803 | 05809 | 05813 | 05818 | 05823 | —     |
| 42   | 12 x 3.3 | —     | —     | 05804 | 05810 | 05814 | 05819 | 05824 | 05830 |
| 48   | 14 x 3.8 | —     | —     | —     | 05811 | 05815 | 05820 | 05825 | 05831 |
| 55   | 16 x 4.3 | —     | —     | —     | —     | 05816 | 05821 | 05826 | 05832 |
| 60   | 18 x 4.4 | —     | —     | —     | —     | —     | 05822 | 05827 | 05833 |
| 70   | 20 x 4.9 | —     | —     | —     | —     | —     | —     | 05828 | 05834 |
| 80   | 22 x 5.4 | —     | —     | —     | —     | —     | —     | 05829 | 05835 |
| 85   | 22 x 5.4 | —     | —     | —     | —     | —     | —     | —     | 05836 |
| 95   | 22 x 5.4 | —     | —     | —     | —     | —     | —     | —     | 05837 |

- Notes:
- Size 1020 thru 1090 hubs are provided with clearance fit bores and 2 set screws at 90°.
  - Lovejoy machines Metric bores and keyways to meet tolerances defined in the ISO 286-2 Standard.
  - When referencing the Lovejoy UPC number in this table, include 697904 as a prefix to the number shown.

GD



**Taper Lock Bushing Hub Torque Ratings and UPC Number Selection Table**

| Grid Coupling Size | Taper-Lock Bushing | Max Bore <sup>1</sup> Bushing in | Max Torque Bushing in-lbs | Rated Torque Coupling in-lbs | LTB   |       | Hub UPC Numbers         |                         |
|--------------------|--------------------|----------------------------------|---------------------------|------------------------------|-------|-------|-------------------------|-------------------------|
|                    |                    |                                  |                           |                              |       |       | UNC <sup>2</sup> Thread | BSW <sup>2</sup> Thread |
| 1030               | 1108               | 1.125                            | 1,300                     | 1,320                        | 1.625 | 41.3  | 06841                   | 06851                   |
| 1040               | 1108               | 1.125                            | 1,300                     | 2,200                        | 1.625 | 41.3  | 06842                   | 06852                   |
| 1050               | 1215               | 1.250                            | 3,550                     | 3,850                        | 1.875 | 47.6  | 06843                   | 06853                   |
| 1060               | 1615               | 1.625                            | 4,300                     | 6,050                        | 2.125 | 54.0  | 06844                   | 06854                   |
| 1070               | 2012               | 2.000                            | 7,150                     | 8,800                        | 2.125 | 54.0  | 06845                   | 06855                   |
| 1080               | 2525               | 2.500                            | 11,300                    | 18,150                       | 2.625 | 66.7  | 06846                   | 06856                   |
| 1090               | 3030               | 3.000                            | 24,000                    | 33,000                       | 3.110 | 79.0  | 06847                   | 06857                   |
| 1100               | 3030               | 3.000                            | 24,000                    | 55,550                       | 3.490 | 88.6  | 06848                   | 06858                   |
| 1110               | 3535               | 3.500                            | 44,800                    | 82,500                       | 3.625 | 92.0  | 06849                   | 06859                   |
| 1120               | 4040               | 4.000                            | 77,300                    | 121,000                      | 4.375 | 111.1 | 06850                   | 06860                   |
| 1130               | 4545               | 4.500                            | 110,000                   | 176,000                      | 4.625 | —     | 18296                   | —                       |

- Notes:
- 1 Indicates: The maximum bore is supplied with a standard ANSI/AGMA 9002-B04 or ISO 286-2 keyway.
  - 2 Indicates: Taper Lock Bushing mounting screws can be either inch (UNC) or metric (BSW) and care should be taken to select the proper hub part number.
  - Taper Lock Bushings are a product of Baldor Dodge and are not included with Lovejoy coupling hubs.
  - Maximum bore size and torque capacities are per Dodge specifications and Lovejoy is not responsible for the accuracy of any of the values listed relative to bore size and torque capacity.
  - When referencing the Lovejoy UPC number in this table, indicate 697904 as prefix to number shown.

**Tapered Component UPC Number Selection Table**

| Sizes →                    | 1020  | 1030  | 1040  | 1050  | 1060  | 1070  | 1080  | 1090  | 1100  | 1110  | 1120  | 1130  | 1140  |
|----------------------------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|
| Grid Only                  | 05244 | 05245 | 05246 | 05247 | 05248 | 05249 | 05250 | 05251 | 05252 | 05253 | 05254 | 05255 | 05256 |
| Horizontal Design:         |       |       |       |       |       |       |       |       |       |       |       |       |       |
| Cover/Grid Assembly-Metric | 05366 | 05367 | 05368 | 05369 | 05370 | 05371 | 05372 | 05373 | 05374 | 05375 | 05376 | 05377 | 05378 |
| Cover/Grid Assembly-Inch   | 05349 | 05350 | 05351 | 05352 | 05353 | 05354 | 05355 | 05356 | 05357 | 05358 | 05359 | 05360 | 05361 |
| Cover Set-Metric           | 05290 | 05291 | 05292 | 05293 | 05294 | 05295 | 05296 | 05297 | 05298 | 05299 | 05300 | 05301 | 05302 |
| Cover Set-Inch             | 05273 | 05274 | 05275 | 05276 | 05277 | 05278 | 05279 | 05280 | 05281 | 05282 | 05283 | 05284 | 05285 |
| Seal Kit                   | 05176 | 05177 | 05178 | 05179 | 05180 | 05181 | 05182 | 05183 | 05184 | 05185 | 05186 | 05187 | 05188 |
| Cover Hardware-Metric      | 05210 | 05210 | 05210 | 05211 | 05211 | 05212 | 05212 | 05212 | 05213 | 05213 | 05214 | 05214 | 05214 |
| Cover Hardware-Inch        | 05433 | 05433 | 05433 | 05434 | 05434 | 05435 | 05435 | 05435 | 05436 | 05436 | 05437 | 05437 | 05437 |
| Vertical Design:           |       |       |       |       |       |       |       |       |       |       |       |       |       |
| Cover/Grid Assembly-Metric | 05400 | 05401 | 05402 | 05403 | 05404 | 05405 | 05406 | 05407 | 05408 | 05409 | 05410 | 05411 | 05412 |
| Cover/Grid Assembly-Inch   | 05383 | 05384 | 05385 | 05386 | 05387 | 05388 | 05389 | 05390 | 05391 | 05392 | 05393 | 05394 | 05395 |
| Cover Set-Metric           | 05328 | 05329 | 05330 | 05331 | 05332 | 05333 | 05334 | 05335 | 05336 | 05337 | 05338 | 05339 | 05340 |
| Cover Set-Inch             | 05307 | 05308 | 05309 | 05310 | 05311 | 05312 | 05313 | 05314 | 05315 | 05316 | 05317 | 05318 | 05319 |
| Seal Kit                   | 05189 | 05190 | 05191 | 05192 | 05193 | 05194 | 05195 | 05196 | 05197 | 05198 | 05199 | 05200 | 05201 |
| Cover Hardware-Metric      | 05215 | 05216 | 05216 | 05217 | 05217 | 05217 | 05218 | 05218 | 05219 | 05219 | 05220 | 05221 | 05222 |
| Cover Hardware-Inch        | 05442 | 05443 | 05443 | 05444 | 05444 | 05444 | 05445 | 05445 | 05446 | 05446 | 05447 | 05448 | 05449 |

- Notes:
- The "Cover/Grid Assembly" includes ALL components of the coupling except the hubs and spacers.
  - The terms "Inch" and "Metric" refer to the hardware (bolts, etc.).
  - The "Cover Set" contains the parts of the Cover/Grid Assembly without the grid spring.
  - The "Seal Kit" contains the rubber seals, gasket(s), and lube plugs.
  - "Cover Hardware" includes the fasteners that hold the cover together.
  - Grease packets are included with all Cover Sets and Cover/Grid Assemblies thru coupling size 1090.
  - When referencing the Lovejoy UPC number in this table, include 697904 as a prefix to the number shown.

**Straight Component UPC Number Selection Table**

| Sizes →                    | 1150  | 1160  | 1170  | 1180  | 1190  | 1200  |
|----------------------------|-------|-------|-------|-------|-------|-------|
| Horizontal Design:         |       |       |       |       |       |       |
| Hub 73mm RSB               | 05587 | —     | —     | —     | —     | —     |
| Hub 100mm RSB              | —     | 05589 | 05591 | —     | —     | —     |
| Hub 125mm RSB              | —     | —     | —     | 05593 | —     | —     |
| Hub 152mm RSB              | —     | —     | —     | —     | 99508 | —     |
| Hub 178mm RSB              | —     | —     | —     | —     | —     | 99257 |
| Grid Only                  | 05257 | 05258 | 05329 | 05260 | 99254 | 99255 |
| Cover/Grid Assembly-Metric | 05379 | 05380 | 05381 | 05382 | 99270 | 10953 |
| Cover/Grid Assembly-Inch   | 05362 | 05363 | 05364 | 05365 | 10555 | 10559 |
| Cover Set-Metric           | 05303 | 05304 | 05305 | 05306 | 99271 | 10951 |
| Cover Set-Inch             | 05286 | 05287 | 05288 | 05289 | 10556 | 10560 |
| Seal Kit                   | 05425 | 05426 | 05427 | 05428 | 10557 | 10561 |
| Cover Hardware-Metric      | 05429 | 05429 | 05430 | 05430 | —     | —     |
| Cover Hardware-Inch        | 05438 | 05438 | 05439 | 05439 | 10558 | 10562 |

- Notes:
- The "Cover/Grid Assembly" includes ALL components of the coupling except the hubs and spacers.
  - The terms "Inch" and "Metric" refer to the hardware (bolts, etc.).
  - The "Cover Set" contains the parts of the Cover/Grid Assembly without the grid spring.
  - The "Seal Kit" contains the rubber seals, gasket(s), and lube plugs.
  - "Cover Hardware" includes the fasteners that hold the cover together.
  - When referencing the Lovejoy UPC number in this table, include 697904 as a prefix to the number shown.